



## Comfortable Fit & Wear

The earcups and headband are adjustable to ensure the perfect fit, while the custom padding provides a soft comfortable fit.

# **■** Built-in Microphone

The built-in microphone is omnidirectional which picks up sound with reliability and is flexble which allows you to adjust the position for optimal performance.

#### Volume Control

With the conveniently located volume control, you can easily adjust the volume at your fingertips.

### Dual 3.5 mm Connectors

The dual 3.5mm connectors allow the headset to work directly with your computer through direct plug and play.







Built-in Microphone



Volume Control



Dual 3.5mm

### Specifications:

Microphone

 $\begin{array}{ll} \mbox{Dimensions:} & 6.0 \times 2.7 \mbox{mm} \, (\Phi) \\ \mbox{Directivity:} & \mbox{Omnidirectional} \\ \mbox{Impedance:} & \leq 2.2 \mbox{k} \Omega \end{array}$ 

Sensitivity: -45±3dB (at 1KHz)

Speaker

 $\begin{array}{ll} \mbox{Driver Diameter:} & \mbox{40mm ($\Phi$)} \\ \mbox{Sensitivity:} & \mbox{105} \pm \mbox{3dB (at 1KHz)} \\ \mbox{Impedance:} & \mbox{32k} \Omega \end{array}$ 

Frequency Response: 20Hz - 20KHz
Cord Length: 6 ft.

Plug: 3.5mm Net Weight: 0.22 lb

#### Includes:

Adesso Xtream H4 Stereo Headset with Microphone Quick Start Guide

#### **Shipping Information:**

| ltem      | UPC Code     | Package Dimensions | Package Weight | Qty/Carton |
|-----------|--------------|--------------------|----------------|------------|
| Xtream H4 | 783750009157 | 6.6" x 8.2" x 2.2" | 0.25 lb        | 10/40      |





